

400 VOLT 50 Hz EMISSIONIZED ENERKIT

ENERKIT MODEL	Voltage	DCP		ESP	
	V	kVA	kWe	kVA	kWe
16M33E1500/5e	400/230	1500	1200	1650	1320
16M33E1750/5e	400/230	1750	1400	1900	1520
16M33E1875/5e	400/230	1875	1500	2000	1650
20M33E2000/5e	400/230	2000	1600	2250	1800
20M33E2500/5e	400/230	2500	2000	2500	2000
12M55E2500/5e	400/230	2500	2000	2750	2200
16M55E2750/5e	400/230	2750	2200	3000	2400
12M55E3000/5e	400/230	3000	2400	3000	2400
16M55E3000/5e	400/230	3000	2400	3300	2640
16M55E3250/5e	400/230	3250	2600	3750	3000
16M55E4125/5e	400/230	4125	3300	4125	3300

400 VOLT 50 Hz UNREGULATED ENERKIT

ENERKIT MODEL	Voltage	DCP		ESP	
	V	kVA	kWe	kVA	kWe
16M33E1500/5	400/230	1500	1200	1650	1320
16M33E1750/5	400/230	1750	1400	1900	1520
16M33E1875/5	400/230	1875	1500	2000	1650
20M33E2000/5	400/230	2000	1600	2250	1800
20M33E2250/5	400/230	2250	1800	2500	2000
12M55E2500/5	400/230	2500	2000	2750	2200
16M55E2750/5	400/230	2750	2200	3000	2400
12M55E3000/5	400/230	3000	2400	3000	2400
16M55E3000/5	400/230	3000	2400	3300	2640
16M55E3250/5	400/230	3250	2600	3750	3000
16M55E4125/5	400/230	4125	3300	4125	3300

*The indicated PRP Power is for reference only



440 VOLT 60 Hz EMISSIONIZED ENERKIT

ENERKIT MODEL	Voltage	DCP		ESP	
	V	kVA	kWe	kVA	kWe
16M33E1400/6e	440/220	1750	1400	1900	1540
16M33E1500/6e	440/220	1875	1500	2065	1650
16M33E1600/6e	440/220	2000	1600	2200	1750
20M33E1800/6e	440/220	2250	1800	2500	2000
12M55E2000/6e	440/220	2500	2000	2750	2200
12M55E2500/6e	440/220	3125	2500	3125	2500
16M55E2400/6e	440/220	3000	2400	3300	2640
16M55E2560/6e	440/220	3200	2560	3520	2800
16M55E2640/6e	440/220	3300	2640	3750	3000
16M55E3300/6e	440/220	4125	3300	4125	3300

440 VOLT 60 Hz UNREGULATED ENERKIT

ENERKIT MODEL	Voltage	DCP		ESP	
	V	kVA	kWe	kVA	kWe
16M33E1400/6	440/220	1750	1400	1900	1540
16M33E1500/6	440/220	1875	1500	2065	1650
16M33E1600/6	440/220	2000	1600	2200	1750
20M33E1800/6	440/220	2250	1800	2500	2000
20M33E2200/6	440/220	2750	2200	2750	2200
12M55E2000/6	440/220	2500	2000	2750	2200
12M55E2500/6	440/220	3125	2500	3125	2500
16M55E2400/6	440/220	3000	2400	3300	2640
16M55E2560/6	440/220	3200	2560	3520	2800
16M55E2640/6	440/220	3300	2640	3750	3000
16M55E3300/6	440/220	4125	3300	4125	3300

*The indicated PRP Power is for reference only

